

# SILO SLIM-LED LINEAR STRIP LIGHT










# Features & Benefits

- 1. Daisy connection with very convenient replacement in 1minute.
- 2. 0-10v dimming, universal voltage: 120-277v or 120-347v.
- 3. Available with suspending installation and surface-mounted installation.
- 4. Wide application for: school, hospital, super market, office and warehouse.
- 5. 2ft, 4ft and 8ft dimensions for variety choices.
- 6. 5-year warranty.

# **Product Dimension**




# **Specification**


Part No.	Power	Input Voltage	Luminous Flux	Luminous Efficacy	ССТ	Viewing Angle	Ra	PF	Warranty
SILO-S-4FT40W-40K SILO-S-4FT40W-40K-MS	40W 40W	110120 2111	5200LM 5200LM	130lm/W	4000K	120°	>80	>0.9	5 YEARS






# Testing Report





# **Applications**











# **Installation manual**

# A.Surface-mounted installation Parts List

# Surface mount kit --2ft (included) Parts: (1) J-box Adapter (2) Anchors (4) Screws Surface mount kit --4ft (included) Parts: (1) J-box Adapter (2) Anchors (4) Screws Surface mount kit --8ft (included) Parts: (1) J-box Adapter (4) Anchors (6) Screws

# **Installation instructions**













2. Swing open fixture by pushing in/squeezing both buttons located on opposite ends.





3.Run the fixture's power wires through the center hole. of the round J-box adapter. Slide and secure the round J-Box adapter on the center slots located on the back of the

Note: J-Box adapter is used to cover the Junction Box





4. Turn off the power and make wiring by using wire nuts according to wiring diagram







5. Secure the fixture to the wall with the correct









7. The installation is completed and energize the luminaire








E468007



# **B. Suspending installation Parts List**


Suspending installation -2FT(included)						
Q Q	Parts: (2) Safety Rope (2) Anchors (2) Screw					
Suspending installation -4FT(included)						
Q Q	Parts: (2) Safety Rope (2) Anchors (2) Screw					
Suspending installation -8FT (inlcuded)						
	Parts: (4) Safety rope (4) Anchors (4) Screw					


# **Installation intructions**




E468007

























# **C.Continuous Row Mounting**

### 4G LED Strip Light Linkable QTY

Size Wa		120V		277V		Suggested
	watts	Current	QTY	Current	QTY	Linkable QTY
4FT						
						≤10PCS
	40W	0.37	13	0.16	30	









# 1.Surface-mounting continuous row mounting(daisy connection) Parts List


## Continuous Row Mounting-2FT(included) Parts: (1) Connection Bracket (1) Harness set (5) Wire Nuts (2) Anchors (2) Screws (2) Self-adhesive Cable Ties Continuous Row Mounting-8FT(included) Parts: (1) Connection Bracket (1) Harness set (5) Wire Nuts (2) Anchors (2) Screws (2) Self-adhesive Cable Ties Continuous Row Mounting-8FT(included) Parts: (1) Connection Bracket (1) Harness set (5) Wire Nuts (4) Anchors (4) Screws (2) Self-adhesive Cable Ties

### Installation instructions












9.Take the black/white/green wire harness and connect to the existing wire connectors on the input wires of the driver respectively. When using the dimming function, take the purple and pink wire harness and make connection to driver. Please make wiring connection using the wiring diagram in Step 8.




10. The same type of electronic wires are inserted into the same wire nut and combined into a parallel circuit.




11. Tighten the wires in the wire nut as the photo shows below.



12. Once wiring is completed, take wire harness and run it thought the knockouts of the connecting fixture. Use self-adhesive cable ties to eliminate any cable tangles and clutter.










# 2. Suspending continuous row mounting(daisy connection)

### Continuous Row Mounting-2FT(included) Parts: (1) Connection Bracket (1) Harness set (5) Wire Nuts (2) Anchors (10) Screws (2) Self-adhesive Cable Ties (2) Safety Rope Continuous Row Mounting-4FT(included) Parts: (1) Connection Bracket (1) Harness set (5) Wire Nuts (2) Anchors (10) Screws (2) Self-adhesive Cable Ties (2) Safety Rope Continuous Row Mounting-8FT(included) (1) Connection Bracket (1) Harness set (5) Wire Nuts (2) Anchors (12) Screws (4) Self-adhesive Cable Ties (2) Safety Rope


### Installation instructions















12. Take the black/white/green wire harness and connect to the existing wire connectors on the input wires of the driver respectively.

When using the dimming function, take the purple and pink wire harness and make connection to driver. Please make wiring connection using the wiring diagram in Step 11.










16. Secure the LED Cover to the housing by pressing upward and lock it into the fixture. Energize the luminaire to verify operation.



E468007